

# 2N381 thru 2N383 (GERMANIUM)

## 2N2171

**CASE 31(1)**  
(TO-5)



Base connected to case

PNP germanium transistors for small-signal audio amplifiers, Class B push-pull output stages and medium-speed switching circuits.

### MAXIMUM RATINGS

Rating	Symbol	Value	Unit
Collector-Base Voltage	$V_{CB}$	50	Volts
Collector-Emitter Voltage ( $R_{BE} = 10K$ )	$V_{CER}$	25	Volts
Emitter-Base Voltage	$V_{EB}$	20	Volts
Collector Current	$I_C$	400	mA
Junction Temperature	$T_J$	-65 to +100	$^{\circ}C$
Collector Dissipation $T_A = 25^{\circ}C$ derate $T_C = 25^{\circ}C$ derate	$P_D$	225 3.0 500 6.7	mW mW/ $^{\circ}C$ mW mW/ $^{\circ}C$

### ELECTRICAL CHARACTERISTICS ( $T_C = 25^{\circ}C$ unless otherwise noted)

Characteristics	Symbol	Min	Typical	Max	Unit
Collector-Base Cutoff Current ( $V_{CB} = -25$ Vdc)	$I_{CBO}$	---	6.0	10	$\mu$ Adc
Emitter-Base cutoff Current ( $V_{EB} = -20$ Vdc)	$I_{EBO}$	---	5.0	10	$\mu$ Adc
Collector-Emitter Voltage ( $I_C = 500 \mu$ Adc, $R_{BE} = 10K$ )	$BV_{CER}$	25	---	---	Vdc
Collector-Emitter Voltage ( $I_C = 50 \mu$ Adc, $V_{BE} = 1.0$ Vdc)	$BV_{CER}$	---	50 45	---	Vdc
DC Current Gain ( $I_C = 20$ mAdc, $V_{CE} = -1.0$ Vdc)	$h_{FE}$	2N381	35	---	65
		2N382	60	---	95
		2N383	75	---	120
		2N2171	110	---	250
( $I_C = 100$ mAdc, $V_{CE} = -1.0$ Vdc)	$h_{FE}$	2N381	30	---	---
		2N382	50	---	---
		2N383	65	---	---
		2N2171	90	---	---

**2N381 thru 2N383 , 2N2171 (continued)**

**ELECTRICAL CHARACTERISTICS (continued)**

Characteristics	Symbol	Min	Typical	Max	Unit
Small Signal Current Gain ( $I_C = 10 \text{ mA}$ , $V_{CE} = -5.0 \text{ V}$ , $f = 1 \text{ kHz}$ )	$h_{fe}$				---
2N381		35	60	85	
2N382		70	90	135	
2N383		90	115	155	
2N2171		120	210	310	
Voltage Feedback Ratio ( $I_C = 10 \text{ mA}$ , $V_{CE} = -5 \text{ V}$ , $f = 1 \text{ kHz}$ )	$h_{re}$				$\times 10^{-3}$
2N381		---	0.66	---	
2N382		---	0.69	---	
2N383		---	0.72	---	
2N2171		---	0.75	---	
Input Impedance ( $I_C = 10 \text{ mA}$ , $V_{CE} = -5.0 \text{ V}$ , $f = 1 \text{ kHz}$ )	$h_{ie}$				ohms
2N381		---	300	---	
2N382		---	450	---	
2N383		---	550	---	
2N2171		---	850	---	
Output Admittance ( $I_C = 10 \text{ mA}$ , $V_{CE} = -5.0 \text{ V}$ , $f = 1 \text{ kHz}$ )	$h_{oe}$				$\mu\text{mhos}$
2N381		---	420	---	
2N382		---	400	---	
2N383		---	380	---	
2N2171		---	500	---	
Transducer Gain ( $R_g = 300 \Omega$ , $R_L = 500 \Omega$ ) ( $R_g = 450 \Omega$ , $R_L = 500 \Omega$ ) ( $R_g = 550 \Omega$ , $R_L = 500 \Omega$ ) ( $R_g = 785 \Omega$ , $R_L = 500 \Omega$ )	$G_T$				dB
2N381		---	36	---	
2N382		---	38	---	
2N383		---	39.5	---	
2N2171		---	42.5	---	
Output Capacitance ( $I_C = 1 \text{ mA}$ , $V_{CB} = -6\text{V}$ )	$C_{ob}$				pF
		---	20	---	
Noise Figure ( $I_C = 1 \text{ mA}$ , $V_{CE} = -6\text{V}$ , $R_g = 1 \text{ kc}$ , $f = 1 \text{ kHz}$ )	NF				dB
2N381		---	6.0	---	
2N382		---	5.5	---	
2N383		---	5.0	---	
2N2171		---	3.5	---	
Cutoff Frequency ( $I_C = 1 \text{ mA}$ , $V_{CB} = -6\text{V}$ )	$f_{\alpha b}$				MHz
2N381		---	3.0	---	
2N382		---	4.0	---	
2N383		---	5.0	---	
2N2171		---	7.5	---	